

Software Information Sheet



JCM American Corporation
 JCM Europe GmbH
 JCM Gold (H.K.) Ltd.
 J-Cash Machine (Thailand) Co., Ltd.
 Japan Cash Machine Co., Ltd. (Headquarters – Japan)

TEL +1-702-651-0000
 TEL +49-211-530-6450
 TEL +852-2429-7187
 TEL +66-2712-3155-6
 TEL +81-6-6703-8405

General Information

Model Name:	EBA-30/34-SD3				SW. Req. No.	C22-0190-01	G20-102		
SW. Name:	EBA-30(CZE-X)-SD3 ID-003				Date: (mm,dd,yyyy)	07.20.2022	Rev:	A1	
SW. Version:	V5.13-32				Note:				
Country (Code):	Czech Republic (CZE)				Guide:				
Currency:	Korun				Check Sum:	307A			
Direction:	4Way				CRC (seed= 0000):	2F46			
Denomination:	Denomi.	Printed	Issued	MRI#	Denomi.	Printed	Issued	MRI#	
Years & MRI Ident 97 th	100	'18	'95-	CZK100.1D					
	200	'18	'96-	CZK200.1D					
	500	'09	'95-	CZK500.1D					
	1000	'08	'96-	CZK1000.1C					
	2000	'07	'96-	CZK2000.1C					
	5000	'99	'99-	CZK5000.1B					
	5000	'09	'99-	CZK5000.1C					
Acceptance Rate:	No less than 90%								
EPROM:	8 Mbit, 100 ns data access, or faster. ST Part M27C801-100F1 or equivalent								
Modifications:	V5.12-32 → V5.13-32								
Validation:	1. Remove acceptance for CZK100.1B/C, CZK200.1B/C, CZK500.1B/C, CZK1000.1B and CZK2000.1A/B								
Operation:									
Interface:									
Memo:	<ul style="list-style-type: none"> - The 5,000 Korun notes acceptance will be disabled automatically when the SD3 operation is selected as their length is out of specification for the operation with the stacker. - The length of the 2,000 Korun notes is also out of specification for the operation with the stacker, so JCM will not be responsible for any damages caused by them during the SD3 operation. - Some of outmoded banknotes cannot be completely removed due to similarities with the new series. 								

Dip Switch Settings

#	Dip Switch 1		Dip Switch 2
1	OFF	Setting Off	Without SD3 operation
	ON	Setting Off	SD3 operation (Not accept 5000 Korun)
2	OFF	Setting Off	Disable optional key switch
	ON	Setting Off	Enable optional key switch
3	OFF	100 ACCEPT	Setting Off
	ON	100 INHIBIT	Setting Off
4	OFF	200 ACCEPT	Setting Off
	ON	200 INHIBIT	Setting Off
5	OFF	500 ACCEPT	Without double paper payout detection
	ON	500 INHIBIT	With double paper payout detection
6	OFF	1000 ACCEPT	Setting Off
	ON	1000 INHIBIT	Setting Off
7	OFF	2000 ACCEPT	Setting Off
	ON	2000 INHIBIT	Setting Off
8	OFF	5000 ACCEPT	Setting Off
	ON	5000 INHIBIT	Setting Off

ID-003 Data Setting specification

VERSION DATA

SW. Version	E(CZE-X)-30-SD3 ID003-05v513-32 20JUL22 2F46
-------------	--

ESCROW DATA

Code	Denomination
61h	Reserved
62h	Reserved
63h	Reserved
64h	100
65h	200
66h	500
67h	1000
68h	2000
69h	5000

CURRENCY ASSIGN DATA

Code	Country	Denomi	Exp.
61h	00h	00h	00h
62h	00h	00h	00h
63h	00h	00h	00h
64h	2Ch	0Ah	01h
65h	2Ch	14h	01h
66h	2Ch	32h	01h
67h	2Ch	64h	01h
68h	2Ch	C8h	01h
69h	2Ch	32h	02h

ENABLE/DISABLE DATA

DATA bit	Data 1	Data 2
0	Reserved	5000
1	Reserved	Reserved
2	Reserved	Reserved
3	100	Reserved
4	200	Reserved
5	500	Reserved
6	1000	Reserved
7	2000	Reserved



0: Enable 1: Disable (Default: **07FEh**)

SECURITY DATA

DATA bit	Data 1	Data 2
0	Reserved	5000
1	Reserved	Reserved
2	Reserved	Reserved
3	100	Reserved
4	200	Reserved
5	500	Reserved
6	1000	Reserved
7	2000	Reserved

0: Normal 1: Security Level high (Default: **0000h**)

DIRECTION DATA

DATA bit	Direction	Sample: 100 Korun	
0	'A' Direction		B
1	'B' Direction		
2	'C' Direction		
3	'D' Direction		
4	Not used		D
5	Not used		
6	Not used		
7	Not used		

0: Not Inhibit 1: Inhibit (Default: **00h**)

OPTIONAL FUNCTION DATA

DATA bit	Data 1	Data 2
0	Hanging Function [01]	Not used
1	Power Recovery [02]	Not used
2	Not used	Not used
3	Not used	Not used
4	Not used	Not used
5	Not used	Not used
6	Not used	Not used
7	Encryption [80]	Not used

0: Disable 1: Enable (Default: **0000h**)

[01] Hanging Function

Rejection of the bill is completed with the end of the bill kept remaining in the acceptor.
(To prevent dropping of the bill)

[02] POWER RECOVERY

Limited to the case where power up status is [POWER UP WITH BILL IN STACKER] with power supply off while ACCEPTOR is in [STACKING] status, [VEND VALID] is outputted in case initializing is completed normally.

Since SETTING STATUS becomes DEFAULT 0000H by power supply off, it is necessary to conduct setting without fail after [RESET] command is transmitted.

[80] Encryption

When "1" is set in the OPTIONAL FUNCTION DATA Bit7, ENCRYPTION will be enabled.

When the ENCRYPTION is enabled, the ESCROW and VEND VALID messages are encrypted.

When banknotes are dispensed, "PAY OUT" and "PAY VALID" are encrypted. The host controller shall encrypt "PAY OUT" command.

For more details, please refer to another document, "ID-003 Encryption Procedure".

© JCM Japan Cash Machine Co., Ltd.	In charge	File: EBA-34_SD3_51332_ID003_CZE.doc	Page: 3/4
---------------------------------------	-----------	---	--------------

Remarks

(1) SECURITY DATA

This function is not enabled even if each denomination is set to “Security level high”.

(2) Operation with SD3 staker: Output timing of [VEND VALID]

When [STACK-1] or [STACK-2] is received, EBA-3x-SD3 will send [VEND VALID] in the following timings:

- * Output timing of [VEND VALID] upon receiving [STACK-1]
EBA-3x-SD3 will send [VEND VALID] after PB unit finishes its operation.
- * Output timing of [VEND VALID] upon receiving [STACK-2]
EBA-3x-SD3 will send [VEND VALID] when a bill is stacked into the cash box.

(3) Operation without SD3 staker: Output timing of [VEND VALID]

EBA-3x will send [VEND VALID] at the timing of [STACK-1], regardless of receiving [STACK-1] or [STACK-2].

(4) Power recovery

Memory backup period for sec power outage is 5 seconds at minimum. For outage of more than 5 seconds, power recovery becomes impossible and the data in memory will be lost.

(5) The following “FAILURE” and “ERROR” status are added on the communication specification for ID-003 4th edition.

*FAILURE Status

FAILURE [0x49] + DATA

DATA	Description
0xa1	Stacking mechanism failure
0xb6	Wrong download file
0xc1	Centering mechanism failure
0xc2	The rollers for centering mechanism do not move up and down
0xc3	Communication error with the staker board

*ERROR Status

[0x4d] Key Unlocked

EBA-3x-SD3 will send this command when the cash box key is unlocked.

EBA-3x-SD3 will initialize itself when the cash box is put into place and the key is locked.

(The key switch is an optional part. EBA-3x-SD3 does not send the error status if the key switch is disabled with dipswitch settings. Bill acceptor does not send this command in operation without SD3 staker.)

[0x4e] Stacker unit separated form acceptor unit

EBA-3x-SD3 will send this command when the staker unit separated form acceptor unit.

EBA-3x-SD3 will initialize itself when the staker unit is put into place.

(EBA-3x-SD3 does not send this command in operation without SD3 staker)